



**DÖRTLER  
KABLO**

www.dkscable.com

## FIRE ALARM CABLES

### Name Of Product

**FIRE ALARM CABLE JY(st)Y**

### Application

These cables are used fire alarm connections in the electronic fire control systems at fixed indoor installations.

### Constractive Data

<b>Conductor</b>	0,82 mm Electrolytic Mono Copper
<b>Insulation</b>	VDE 0815'according PVC
<b>Bend</b>	CORES TWISTED IN LAYERS
<b>Screen</b>	PES-BAND+0,82 mm TINNED DRAIN WIRE+ AL-PES BAND
<b>Outer Sheat</b>	PVC Red
<b>Packing</b>	100 mt. Coil, 500-1000 mt. Reel

### Electrical Data

<b>Conductor Resistance</b>	73,2 $\Omega$ /km
<b>Insulation Resistance</b>	>100 M $\Omega$ /km
<b>Capacitance</b>	100 nf/km
<b>Operating Voltage</b>	300 V
<b>Test Voltage</b>	800 V
<b>Bending Radius</b>	10x Kablo $\emptyset$
<b>Operating Temperature</b>	- 30°C.....+70°C

### PRODUCT SECTION

1x2x0.80+0.80

### OUTHER SHEAT DIA

4,70 mm

### 100 mt Weight

3,35 kg



Bir Dörtler kablo ürünüdür

**Ar-Ge  
Kablo**